

## New functions and addendum

This document contains descriptions of how to set the new functions and their restrictions of WV-V2530LK\_WV-V2530L1\_WV-V1330LK\_WV-V1330L1.

It is recommended to read them while referring to the Operating Instructions provided with this product together.

Due to software upgrade, the following functions have been added and changed to this product.

·Firmware Ver.2.61

No.	Functions	Item (Page)	Page
1	Addition of Panasonic alarm protocol notification	Notification (Event)	1

### 1. Notification

Add the settings relating to Panasonic alarm protocol notification can be configured in this section. See ch.6.4.5 of Operating Instructions.

The screenshot shows a web-based configuration interface for a Panasonic device. The left sidebar contains a navigation menu with categories: Live, Setup, Basic, Image/Audio, Network, Event, Storage, System, and Information. The 'Event' category is expanded, showing sub-items: Video Detection, Audio Detection, Alarm, Abnormality, and Notification (highlighted in green). The main content area is titled 'Notification' and contains the following settings:

- Panasonic alarm protocol notification**
  - Panasonic alarm protocol: Radio buttons for ON and OFF. OFF is selected.
  - Destination port: Text input field containing '1818' with a range '(1~65535)'.
  - Retry times: Dropdown menu set to '2'.
- Destination of notification** (table):

Destination of notification	Alarm	Destination server address
Address 1	<input type="checkbox"/>	0 . 0 . 0 . 0
Address 2	<input type="checkbox"/>	0 . 0 . 0 . 0
Address 3	<input type="checkbox"/>	0 . 0 . 0 . 0
Address 4	<input type="checkbox"/>	0 . 0 . 0 . 0
Address 5	<input type="checkbox"/>	0 . 0 . 0 . 0
Address 6	<input type="checkbox"/>	0 . 0 . 0 . 0
Address 7	<input type="checkbox"/>	0 . 0 . 0 . 0
Address 8	<input type="checkbox"/>	0 . 0 . 0 . 0

At the bottom of the configuration area are three buttons: Default, Refresh, and Save.

#### Panasonic alarm protocol notification

[Panasonic alarm protocol]

Select "ON" or "OFF" to determine whether or not to provide notification by Panasonic alarm protocol according to the settings for the "Alarm" checkboxes of "Destination of notification" below.

- When an alarm is detected ("Alarm")
- Default: OFF

#### Note

When "ON" is selected, notification of the alarm occurrence will be provided to the registered destination server addresses in order (to IP address 1 first, to IP address 8

last).

[Destination port]

Select a destination port for the Panasonic alarm protocol from the following.

- Available range: 1 - 65535
- Default: 1818

[Retry times]

Select a retry time for the Panasonic alarm protocol.

- Available range: 0-30
- Default: 2

Destination of notification

[Address 1] - [Address 8]

Enter the destination IP address of the Panasonic alarm protocol from the following. Up to 8 destination server addresses can be registered.

- [Alarm] checkbox: When the checkbox is checked, the Panasonic alarm notification will be provided upon an alarm occurrence.

[Destination server address]: Enter the destination server address.